

## FISA TEHNICA

# Teu bransament electrofuziune

**Categorie:** Fitinguri electrofuziune Teuri si sei bransament electrofuziune



Cod: 496304

- Material : PE100 virgin , PE100RC virgin , culoare neagra
- Compatibilitate material : PE100 , PE100RC , PE80 , PEX
- Presiuni de lucru : PN10 Gaz , PN16 Apa (PE100 SDR11)
- Durata viata : minim 50 ani
- Respecta prevederile EN1555 si EN12201 respectiv ISO4437 si ISO4427
- Fabricate prin injectie in matrite
- Conectori sudare 4 mm
- Martori sudura incorporati

| d<br>mm | d1<br>mm | B<br>mm | H<br>mm | H1<br>mm | H2<br>mm | L<br>mm | Presiunde de<br>lucru<br>Gaz | Presiune de<br>lucru<br>Apa | Tip | Tevi  | Tip capac<br>sudură | Greutate<br>g | Buc/cutie |
|---------|----------|---------|---------|----------|----------|---------|------------------------------|-----------------------------|-----|-------|---------------------|---------------|-----------|
| 40      | 25       | 65      | 90      | 7        | 98       | 100     | PE100 SDR 11                 | PN 16                       | mb  | SDR11 | Tip C               | 349           | 52        |
| 40      | 32       | 66      | 121     | 11       | 94       | 100     | PE100 SDR 11                 | PN 16                       | mb  | SDR11 | Tip C               | 370           | 52        |
| 40      | 20       | 66      | 107     | 7        | 94       | 100     | PE100 SDR 11                 | PN 16                       | mb  | SDR11 | Tip C               | 290           | 52        |
| 50      | 20       | 76      | 110     | 7        | 98       | 100     | PE100 SDR 11                 | PN 16                       | mb  | SDR11 | Tip C               | 390           | 52        |
| 50      | 25       | 76      | 91      | 10       | 98       | 100     | PE100 SDR 11                 | PN 16                       | mb  | SDR11 | Tip C               | 390           | 50        |
| 50      | 32       | 76      | 122     | 12       | 98       | 100     | PE100 SDR 11                 | PN 16                       | mb  | SDR11 | Tip C               | 390           | 45        |
| 63      | 20       | 100     | 90      | 10       | 90       | 118     | PE100 SDR 11                 | PN 16                       | mb  | SDR11 | Tip C               | 362           | 40        |
| 63      | 25       | 100     | 93      | 12       | 36       | 118     | PE100 SDR 11                 | PN 16                       | mb  | SDR11 | Tip C               | 364           | 40        |
| 63      | 32       | 100     | 99      | 12       | 90       | 118     | PE100 SDR 11                 | PN 16                       | mb  | SDR11 | Tip C               | 380           | 40        |
| 63      | 40       | 100     | 142     | 64       | 177      | 118     | PE100 SDR 11                 | PN 16                       | -   | SDR11 | Tip A               | 870           | 16        |
| 63      | 50       | 100     | 154     | 64       | 177      | 118     | PE100 SDR 11                 | PN 16                       | -   | SDR11 | Tip A               | 1099          | 16        |
| 63      | 63       | 100     | 175     | 64       | 177      | 118     | PE100 SDR 11                 | PN 16                       | -   | SDR11 | Tip A               | 962           | 16        |
| 75      | 63       | 117     | 175     | 64       | 177      | 118     | PE100 SDR 11                 | PN 16                       | -   | SDR11 | Tip A               | 1228          | 16        |
| 75      | 50       | 117     | 123     | 64       | 177      | 118     | PE100 SDR 11                 | PN 16                       | -   | SDR11 | Tip A               | 1140          | 16        |
| 75      | 32       | 117     | 132     | 56       | 177      | 118     | PE100 SDR 11                 | PN 16                       | -   | SDR11 | Tip A               | 1091          | 16        |
| 75      | 20       | 117     | 125     | 50       | 177      | 118     | PE100 SDR 11                 | PN 16                       | -   | SDR11 | Tip A               | 1120          | 16        |

## FISA TEHNICA

|     |    |     |     |    |     |     |              |       |    |                 |       |      |    |
|-----|----|-----|-----|----|-----|-----|--------------|-------|----|-----------------|-------|------|----|
| 75  | 40 | 117 | 142 | 60 | 177 | 118 | PE100 SDR 11 | PN 16 | -  | SDR11           | Tip A | 1124 | 16 |
| 90  | 20 | 126 | 117 | 16 | 114 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip B | 900  | 20 |
| 90  | 25 | 126 | 108 | 16 | 114 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip B | 1120 | 20 |
| 90  | 32 | 126 | 126 | 16 | 114 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip B | 778  | 20 |
| 90  | 40 | 126 | 134 | 21 | 114 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip B | 1130 | 20 |
| 90  | 50 | 126 | 123 | 64 | 177 | 118 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1220 | 14 |
| 90  | 63 | 126 | 175 | 64 | 177 | 118 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1300 | 14 |
| 110 | 20 | 148 | 119 | 16 | 114 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip B | 964  | 20 |
| 110 | 63 | 148 | 175 | 64 | 177 | 118 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1383 | 12 |
| 110 | 50 | 148 | 123 | 64 | 177 | 118 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1300 | 12 |
| 110 | 40 | 148 | 138 | 21 | 114 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip B | 1000 | 20 |
| 110 | 32 | 148 | 127 | 16 | 114 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip B | 970  | 20 |
| 110 | 25 | 148 | 118 | 16 | 114 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip B | 830  | 20 |
| 125 | 63 | 162 | 175 | 64 | 177 | 118 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1426 | 12 |
| 125 | 50 | 162 | 123 | 64 | 177 | 118 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1345 | 12 |
| 125 | 40 | 162 | 141 | 21 | 114 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip B | 1280 | 15 |
| 125 | 25 | 162 | 131 | 16 | 114 | 118 | PE100 SDR 12 | PN 16 | mb | SDR 7 to SDR 17 | Tip B | 1220 | 15 |
| 125 | 20 | 162 | 116 | 16 | 114 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip B | 1220 | 15 |
| 125 | 32 | 162 | 131 | 16 | 114 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip B | 899  | 15 |
| 140 | 32 | 180 | 132 | 56 | 177 | 118 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1330 | 12 |
| 140 | 40 | 180 | 142 | 60 | 177 | 118 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1360 | 12 |
| 140 | 50 | 180 | 123 | 64 | 177 | 118 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1382 | 12 |
| 140 | 63 | 180 | 175 | 64 | 177 | 118 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1468 | 12 |
| 160 | 20 | 199 | 118 | 21 | 138 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip A | 1360 | 10 |
| 160 | 25 | 199 | 100 | 21 | 138 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip A | 1170 | 10 |
| 160 | 32 | 199 | 144 | 16 | 138 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip A | 1320 | 10 |
| 160 | 40 | 199 | 157 | 21 | 138 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip A | 1216 | 10 |
| 160 | 50 | 199 | 175 | 24 | 138 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip A | 1375 | 10 |
| 160 | 63 | 199 | 197 | 20 | 138 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip A | 1390 | 10 |
| 180 | 50 | 219 | 174 | 24 | 138 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip A | 1595 | 10 |
| 180 | 63 | 219 | 197 | 20 | 138 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip A | 1605 | 10 |
| 180 | 40 | 219 | 155 | 21 | 138 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip A | 1274 | 10 |

## FISA TEHNICA

|     |    |     |     |    |     |     |              |       |    |                 |       |      |    |
|-----|----|-----|-----|----|-----|-----|--------------|-------|----|-----------------|-------|------|----|
| 180 | 25 | 219 | 110 | 18 | 138 | 118 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1100 | 10 |
| 180 | 20 | 219 | 125 | 50 | 177 | 118 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1550 | 10 |
| 180 | 32 | 219 | 144 | 18 | 138 | 118 | PE100 SDR 11 | PN 16 | mb | SDR 7 to SDR 17 | Tip A | 1565 | 10 |
| 200 | 20 | 202 | 125 | 50 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1425 | 8  |
| 200 | 32 | 202 | 132 | 56 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1451 | 8  |
| 200 | 40 | 202 | 142 | 60 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1471 | 8  |
| 200 | 50 | 202 | 123 | 64 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1496 | 8  |
| 200 | 63 | 202 | 175 | 64 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1579 | 8  |
| 225 | 32 | 227 | 132 | 56 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1450 | 8  |
| 225 | 63 | 227 | 175 | 64 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1589 | 8  |
| 225 | 50 | 227 | 123 | 64 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1506 | 8  |
| 225 | 40 | 227 | 142 | 60 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1485 | 8  |
| 225 | 20 | 227 | 125 | 50 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1370 | 8  |
| 250 | 20 | 252 | 125 | 50 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1455 | 8  |
| 250 | 32 | 252 | 132 | 56 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1464 | 8  |
| 250 | 40 | 252 | 142 | 60 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1582 | 8  |
| 250 | 50 | 252 | 123 | 64 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1589 | 8  |
| 250 | 63 | 252 | 175 | 64 | 177 | 176 | PE100 SDR 11 | PN 16 | -  | SDR 7 to SDR 17 | Tip A | 1386 | 8  |