

FISA TEHNICA

Teu redus electrofuziune

Categorie: [Fitinguri electrofuziune](#) [Teuri electrofuziune](#)



Cod: 491404

- Material : PE100 virgin , PE100RC virgin , culoare neagra
- Compatibilitate material : PE100 , PE100RC , PE80 , PEX
- Presiuni de lucru : PN10 Gaz , PN16 Apa (PE100 SDR11)
- Durata viata : minim 50 ani
- Respecta prevederile EN1555 si EN12201 respectiv ISO4437 si ISO4427
- Fabricate prin injectie in matrite
- Conectori sudare 4 mm
- Martori sudura incorporati

d mm	d1 mm	A mm	D mm	H mm	L mm	L1 mm	Presiune de lucru Gaz	Presiune de lucru Apa	Tevi	Greutate g	Buc/punga	Buc/cutie
25	32	43	44	74	104	39	PE100 SDR 11	PN 16	SDR 7 to SDR 11	120	1	168
25	20	43	44	66	104	39	PE100 SDR 11	PN 16	SDR 7 to SDR 11	110	1	168
32	20	43	44	66	104	39	PE100 SDR 11	PN 16	SDR 7 to SDR 11	90	1	144
32	25	43	44	66	104	39	PE100 SDR 11	PN 16	SDR 7 to SDR 11	90	1	144
40	20	47	56	72	120	43	PE100 SDR 11	PN 16	SDR 7 to SDR 17	150	1	96
40	25	47	56	72	120	43	PE100 SDR 11	PN 16	SDR 7 to SDR 17	150	1	96
40	32	47	56	75	120	43	PE100 SDR 11	PN 16	SDR 7 to SDR 17	150	1	96
50	40	52	68	90	139	48	PE100 SDR 11	PN 16	SDR 7 to SDR 17	240	1	64
50	32	52	68	86	139	48	PE100 SDR 11	PN 16	SDR 7 to SDR 17	230	1	64
50	25	52	68	78	139	48	PE100 SDR 11	PN 16	SDR 7 to SDR 17	230	1	64
50	20	52	68	78	139	48	PE100 SDR 11	PN 16	SDR 7 to SDR 17	220	1	64

FISA TEHNICA

63	20	58	82	85	167	49	PE100 SDR 11	PN 16	SDR 7 to SDR 17	350	1	40
63	32	58	82	93	167	58	PE100 SDR 11	PN 16	SDR 7 to SDR 17	350	1	32
63	40	58	82	104	167	58	PE100 SDR 11	PN 16	SDR 7 to SDR 17	370	1	32
63	50	58	82	109	167	58	PE100 SDR 11	PN 16	SDR 7 to SDR 17	380	1	32
75	63	62	96	122	196	63	PE100 SDR 11	PN 16	SDR 7 to SDR 17	610	1	26
90	63	71	113	124	294	68	PE100 SDR 11	PN 16	SDR 7 to SDR 17	1050	1	15
90	75	71	112	137	293	71	PE100 SDR 11	PN 16	SDR 7 to SDR 17	1050	1	15
110	63	81	143	134	326	71	PE100 SDR 11	PN 16	SDR 7 to SDR 17	1720	1	9
110	90	81	143	147	326	71	PE100 SDR 11	PN 16	SDR 7 to SDR 17	1820	1	8
110	75	81	143	142	328	72	PE100 SDR 11	PN 16	SDR 7 to SDR 17	2160	1	9
125	90	88	165	161	382	86	PE100 SDR 11	PN 16	SDR 7 to SDR 17	2810	1	5
125	110	88	165	173	382	86	PE100 SDR 11	PN 16	SDR 7 to SDR 17	2860	1	5
160	90	105	209	192	396	97	PE100 SDR 11	PN 16	SDR 7 to SDR 17	4190	1	3
160	110	106	208	193	440	86	PE100 SDR 11	PN 16	SDR 7 to SDR 17	4470	1	3
160	125	105	209	214	396	97	PE100 SDR 11	PN 16	SDR 7 to SDR 17	4470	1	3
180	125	116	245	225	422	106	PE100 SDR 11	PN 16	SDR 7 to SDR 17	6410	1	2
180	160	116	245	250	422	106	PE100 SDR 11	PN 16	SDR 7 to SDR 17	6950	1	1
180	140	116	245	237	422	106	PE100 SDR 11	PN 16	SDR 7 to SDR 17	6610	1	1
180	110	116	245	219	422	106	PE100 SDR 11	PN 16	SDR 7 to SDR 17	6270	1	2
180	90	116	245	200	422	106	PE100 SDR 11	PN 16	SDR 7 to SDR 17	6090	1	2
200	90	125	261	205	451	114	PE100 SDR 11	PN 16	SDR 7 to SDR 17	7140	1	2
200	110	125	261	210	451	114	PE100 SDR 11	PN 16	SDR 7 to SDR 17	7240	1	2
225	90	140	293	220	494	122	PE100 SDR 11	PN 16	SDR 7 to SDR 17	9900	1	1
225	110	140	293	225	494	122	PE100 SDR 11	PN 16	SDR 7 to SDR 17	10000	1	1
250	90	152	326	235	538	129	PE100 SDR 11	PN 16	SDR 7 to SDR 17	13350	1	1
250	110	152	326	240	538	129	PE100 SDR 11	PN 16	SDR 7 to SDR 17	13400	1	1